

INTEGRATED INDUCTOR AND ELECTRONIC CIRCUIT  
INCORPORATING THE SAME

**Inventor(s) :**

Bart Van Haaren  
Bâtiment 1  
Le clos de Gagoux  
38120 Le Touvet  
FRANCE  
Dutch citizen

Cécile Clement  
626 avenue de l'Abbaye  
38920 Grenoble  
FRANCE  
French citizen

Daniel Gloria  
Appt. B11  
53b rue Pierre Semard  
38000 Grenoble  
FRANCE  
French citizen

**Assignee:**

STMICROELECTRONICS SA  
29 Boulevard Raymond Rolland  
92120 Montrouge  
FRANCE

William A. Munck  
DAVIS MUNCK, P.C.  
Three Galleria Tower  
13155 Noel Road, Suite 900  
Dallas, Texas 75240  
(972) 628-3600

**INTEGRATED INDUCTOR AND ELECTRONIC CIRCUIT  
INCORPORATING THE SAME**

**TECHNICAL FIELD OF THE INVENTION**

5        [0001] The present invention relates generally to inductors used in integrated electronic components. More particularly, the present invention relates to a substantially plane integrated inductor made on the surface of a substrate.

10

**BACKGROUND OF THE INVENTION**

      [0002] The cost of manufacturing an integrated electronic circuit comprising such an integrated inductor is strongly associated with the level of integration of the electronic elements forming it. In some applications, it is necessary to have available several inductance values in one and the same integrated circuit. Different inductors are then produced on the surface of the substrate, each one having a respective inductance.

20        [0003] A need exists in the art to increase the level of integration of the integrated circuit, and therefore to allow the manufacturing costs of such a circuit to be reduced in this type of application.

SUMMARY OF THE INVENTION

[0004] To address the above-discussed deficiencies of the prior art, a first aspect of the invention relates to an integrated inductor of the aforementioned type  
5 which further comprises at least a second pair of access points different from the access points of the first pair, and placed at two respective regions of the first conducting track.

[0005] As such, the first conducting track has  
10 respective inductance values between each pair of access points. For example, if it has two pairs of access points, it has a first inductance value between the first pair of access points and a second inductance value between the second pair of access points. An inductor  
15 according to the invention thus makes it possible advantageously to replace two inductors according to the prior art, or even more by increasing the number of pairs of access points.

[0006] In one advantageous embodiment, the shape of  
20 the first conducting track has an axial symmetry having as axis of symmetry the perpendicular bisector of the segment formed by the access points of the first pair of access points.

[0007] Preferably, the said axis of symmetry of the  
25 first conducting track is in addition the perpendicular bisector of the segment formed by the access points of

the second pair of access points.

[0008] The portions of the first conducting track giving the first inductance value, or the first and second inductance values, thus have symmetrical geometry with respect to their respective pair of access points. Such inductance values may be used in differential structures, for example a differential oscillator or amplifier.

[0009] Preferably, the integrated inductor further comprises a second substantially straight conducting track having an axis coincident with the axis of symmetry of the first conducting track, and electrically connected to the first conducting track in a region corresponding to the middle of the extended length of the said first conducting track, together with a first additional access point corresponding to a first end of the second conducting track.

[00010] This first end, which then corresponds to the "mid-point" of the first inductance value, is for example placed between the access points of the first pair of access points (in the plane of the integrated inductor), and preferably in the middle.

[00011] In an advantageous embodiment, the integrated inductor further comprises a second additional access point corresponding to a second end of the second conducting track.

[00012] This second end, which corresponds to the "mid-point" of the second inductance value, is for example placed between the access points of the second pair of access points (in the plane of the integrated inductor), and preferably in the middle.

[00013] In an exemplary embodiment, the access points of the second pair of access points are located respectively at approximately one quarter and three quarters of the extended length (in the plane of the integrated inductor) of the first conducting track.

[00014] The inductance value between the access points of the first pair of access points is then close to twice the inductance value between the access points of the second pair of access points.

[00015] In preferred embodiments of the invention, one and/or other of the following arrangements may optionally be used:

- the turns of the first conducting track are polygonal.
- the turns of the first conducting track are octagonal.

[00016] A second aspect of the invention relates to an integrated electronic circuit which comprises an integrated inductor according to the first aspect.

[00017] A third aspect of the invention relates to an

5

integrated electronic circuit which comprises an integrated inductor according to the first aspect and means for applying currents in phase opposition respectively to each of the access points of the first pair of access points, and/or means for applying currents in phase opposition respectively to each of the access points of the second pair of access points, the first additional access point and/or the second additional access point being taken to a neutral electrical potential, typically earth.

[00018] Before undertaking the DETAILED DESCRIPTION OF THE INVENTION below, it may be advantageous to set forth definitions of certain words and phrases used throughout this patent document: the terms "include" and "comprise," as well as derivatives thereof, mean inclusion without limitation; the term "or," is inclusive, meaning and/or; and the phrases "associated with" and "associated therewith," as well as derivatives thereof, may mean to include, be included within, interconnect with, contain, be contained within, connect to or with, couple to or with, be communicable with, cooperate with, interleave, juxtapose, be proximate to, be bound to or with, have, have a property of, or the like. Definitions for certain words and phrases are provided throughout this patent document, those of ordinary skill in the art should understand that in many,

6

if not most instances, such definitions apply to prior,  
as well as future uses of such defined words and phrases.

**BRIEF DESCRIPTION OF THE DRAWINGS**

[00019] Other features and advantages of the present invention will become apparent during the following description of one of its embodiments, given by way of non-limiting example, with reference to the appended drawings, in which like reference numerals represent like parts, and in which:

Figure 1 is a top view of a first embodiment of an integrated inductor according to the invention;

10        Figure 2 is the corresponding circuit diagram of an integrated inductor according to the invention; and

Figure 3 is a top view of a second embodiment of an integrated inductor according to the invention.



**DETAILED DESCRIPTION OF THE INVENTION**

[00020] FIGURES 1 through 3, discussed below, and the various embodiments used to describe the principles of the present invention in this patent document are by way of illustration only and should not be construed in any way to limit the scope of the invention. Those skilled in the art will understand that the principles of the present invention may be implemented in any suitably arranged inductors used in integrated electronic components.

[00021] Figure 1 shows a top view of an integrated inductor 1, in a first embodiment of the invention. This inductor 1 is made on the surface of a substrate 3, according to techniques known to a person skilled in the art. The inductor 1 is substantially plane. For the sake of simplicity, in the present account of the invention, the geometry of the inductor 1 is described in a two-dimensional manner by considering a single plane corresponding to the surface of the substrate 3. Of course, various parts of the inductor are in general, and in a manner known per se, made in respective metallization levels.

[00022] The inductor 1 comprises a first conducting track 2. This track lies, for example, in a determined metallization level (corresponding to the plane of the figure), made above a semiconductor substrate.

[00023] In the example corresponding to Figure 1, the track 2 forms two concentric turns 4 and 5 having centre O and radius  $R_1$  and  $R_2$ , respectively. Here, these radii are measured from the inner edge of the track 2. The turns are preferably of polygonal shape. Here, they are of octagonal shape. Furthermore, the track 2 has an axial symmetry with respect to an axis X-X passing through the centre O of the turns. Passage from the turn 4 to the turn 5 without contact between the two turns takes place by inserting an air bridge 10 or "underpass", in another metallization level, which is below the plane of the figure in the example shown but which may also be above this plane.

[00024] The inductor 1 comprises a first pair of access points 6 and 6' corresponding to the ends of the track 2. Preferably, these points are arranged symmetrically on each side of the axis X-X. The track 2 has an inductance value  $L_1$  between the pair of access points 6 and 6'.

[00025] The inductor 1 further comprises another pair of access points 7 and 7' placed at two regions 14 and 15 respectively of the conducting track 2. The track 2 has an inductance value  $L_2$  between the access points 7 and 7'.

[00026] In the exemplary embodiment of the invention in question, the access points 7 and 7' are placed

10

symmetrically on each side of the axis X-X. In other words, this axis is also the perpendicular bisector of the segment formed by the points 7 and 7', such that the geometry of the inductor 1 is symmetrical with respect to  
5 the axis X-X'. Furthermore, the points 7 and 7' are located respectively at approximately a quarter and three quarters of the extended length of the track 2. Thus L1 is close to twice L2.

[00027] Furthermore, the inductor 1 may comprise a  
10 second track 8 which, in the embodiment shown, is straight. The track 8 is located, in the example shown, in a metallization level below the plane of Figure 1. If the plane of the inductor 1 is considered overall, it can be said that the track 8 lies along the axis X-X. In this  
15 sense, it can be said that the longitudinal axis of the track 8 coincides with the axis of symmetry X-X' of the track 2 in the plane thereof.

[00028] The track 8 is electrically connected to the first track 2 in a region M corresponding to the middle  
20 of the extended length of the conducting track 2. This electrical connection takes place, for example, by means of an electrical connection 9 (or via) arranged perpendicularly to the plane of the track 2. This region M therefore corresponds to the middle of the portion of  
25 track between the access points 6 and 6', and to the middle of the portion of track between the access points

7 and 7'.

[00029] The second track 8 comprises two ends 11 and 12, one and/or other of which correspond(s) to respective additional access points of the inductor 1. These access  
5 points 11 and 12 are arranged such that the orthogonal projection of the access point 11 onto the plane of the track 2 is located between, and preferably in the middle of, the pair of access points 6 and 6', and such that the orthogonal projection of the access point 12 onto the  
10 plane of the track 2 is located between, and preferably in the middle of, the pair of access points 7 and 7'.

[00030] Figure 2 shows a circuit diagram equivalent to the use in differential mode of the inductance values L1 and L2 of the inductor 1. It will be recalled that the  
15 inductor 1 has, between the access points 6 and 6', the inductance value L1 and a central access point 11. It also has, between the access points 7 and 7', an inductance value L2 and a central access point 12. These central access points 11 and 12 are typically connected  
20 to a neutral potential such as earth and currents +I and -I are applied in phase opposition respectively to each of the access points 6 and 6', and currents +I' and -I' are applied in phase opposition respectively to each of the access points 7 and 7'.

25 [00031] An integrated inductor of the inductor type shown in Figures 1 and 2 and described above, with the

12

inductance value L1 greater than the inductance value L2, may for example be used in order to produce an integrated circuit of the multiband VCO (Voltage Controlled Oscillator) type in differential mode, equivalent to two  
5 VCOs at different frequencies (in this case, about double), for example 1.8 GHz and 0.9 GHz.

[00032] Thus, the invention effectively makes it possible to increase the level of integration of an integrated circuit and therefore to reduce the cost of  
10 manufacturing such a circuit.

[00033] Figure 3 shows a top view of an integrated inductor 1' according to another embodiment of the invention. The inductor 1' shown in Figure 3 differs from the inductor 1 shown in Figure 1 in that the track 2  
15 comprises not two but three concentric turns 4, 5 and 13, in this case, of octagonal shape. Passage of the track 2 from the turn 4 to the turn 5 without contact between the two turns takes place by inserting an air bridge 10. In the same way, passage of the track 2 from the turn 5 to  
20 the turn 13 without contact between the two turns takes place by inserting an air bridge 10'. These air bridges 10 and 10' are located in other metallization levels, which are below the plane of the figure in the example shown, but which may also be above.

25 [00034] The inductor 1' still comprises a first pair of access points 6 and 6' corresponding to the ends of

13

the track 2 and placed symmetrically on each side of the axis X-X. The track 2 has an inductance value  $L_1$  between the pair of access points 6 and 6'.

[00035] The inductor 1' still comprises another pair of access points 7 and 7' placed at two respective regions 14 and 15 of the conducting track 2. The track 2 has an inductance value  $L_2$  between the access points 7 and 7'.

[00036] In the exemplary embodiment of the invention considered in Figure 3, the access points 7 and 7' are still arranged symmetrically on each side of the axis X-X. However, they are located respectively at about one fifth and four-fifths of the extended length of the conducting track 2. Thus the inductance value  $L_2$  is close to three fifths of the inductance value  $L_1$ .

[00037] As in the case of the inductor 1 shown in Figure 1, the inductor 1' further comprises a second track 8 which comprises two ends corresponding to two additional access points 11 and 12, arranged in the same way as in Figure 1. The track 8 is electrically connected by means of an electrical connection 9 to the centre of the conducting track 2 in a region M which corresponds to the middle of the portion of track between the access points 6 and 6', and to the middle of the portion of track between the access points 7 and 7'.